



UP - VW0645P1

Model No	UP - VW0645P1
Selling Unit	EACH
Description	UP - VW0645P1 (UP - RW0645P1) Panasonic Sealed Lead Acid Battery for Standby, UPS
Application	Standby, UPS
Chemistry	Sealed Lead
Voltage	6V
Watt Hour	54Wh
Watts Per Cell	45W
Nominal Capacity	9Ah
Termination	F2, Faston 250 6.3mm (0.25") spade terminals
Width	34mm
Height	94mm
Length/Breadth/Depth	151mm
Weight	1300g
Outer Quantity	12

Suitable For:	APC BACK-UPS Powerstack 450 (2 Batteries Required)	MGE Pulsar Evolution 1500 Rack (6 batteries required)	Tripp Lite BC205A (1 Battery Required)
	APC BACK-UPS Powerstack PS250 (2 Batteries Required)	MGE Pulsar Evolution 500 (2 batteries required)	Tripp Lite BC 275 (3 Batteries Required)
	APC BACK-UPS Powerstack PS450 (2 Batteries Required)	MGE Pulsar Evolution 800 Rack (4 batteries required)	Tripp Lite BC350 (3 Batteries Required)
	APC Power Stack 250 (2 Batteries Required)	Minuteman E1000RM1U (4 batteries required)	Tripp Lite BC375 (1 Battery Required)
	APC PS250 (2 Batteries Required)	Minuteman E1500RM1U (4 batteries required)	Tripp Lite BC400 (1 Battery Required)
	APC PS450 (2 Batteries Required)	Minuteman E700RM1U (4 batteries required)	Tripp Lite BC400A (3 Batteries Required)
	APC SMART-UPS Powerstack 250VA (2 Batteries Required)	Powerware Powerware Personal 500 (3 Batteries Required)	Tripp Lite BC450D (3 Batteries Required)
	APC SMART-UPS Powerstack 450VA (2 Batteries Required)	Powerware Powerware PW5119-1000 (4 Batteries Required)	Tripp Lite BC500/A (3 Batteries Required)
	APC SMART-UPS RM PS250 (2 Batteries Required)	Powerware Powerware PW5119-2000 (8 Batteries Required)	Tripp Lite BC500ALAN (3 Batteries Required)
	APC SMART-UPS RM PS450 (2 Batteries Required)	Powerware Powerware PW9120 BAT-1000 (6 Batteries Required)	Tripp Lite Datashield T2+450 (2 Batteries Required)
	MGE ES4 (1 Battery Required)	Powerware Powerware PW9120 BAT-1500 (8 Batteries Required)	Upsonic ES 1RU 1000 (4 batteries required)
	MGE ESV5 (2 Batteries Required)	Powerware Powerware PW9120 BAT-3000 (1 Battery Required)	Upsonic ES 1RU 1500 (4 batteries required)
	MGE Pulsar EL2 (2 Batteries Required)	Powerware Powerware PW9120 Bat-700 (4 Batteries Required)	Upsonic Slim 1000 (2 Batteries Required)
	MGE Pulsar EL4 (2 Batteries Required)	Powerware/Exide Exide Personal 500 (3 Batteries Required)	Upsonic SW 1000 (2 Batteries Required)
	MGE Pulsar Evolution 1100 Rack (4 batteries required)	Tripp Lite BC205 (1 Battery Required)	Upsonic UPS Slim 1000 (2 Batteries Required)
	Comments		

This battery is specifically designed for standby use. Ideal for security, fire panels and Uninterruptible Power Supply (UPS) use.

Not recommended for cyclic use.

Former model – UP-RW0645P1. New model in flame retardant case (UL94V-0). Replaces UP-RW0645P1. Master Instruments is proud to be the official major distributor for Panasonic industrial batteries including Panasonic sealed lead acid (VRLA) batteries in Australia on behalf of [Panasonic Storage Battery \(Shenyang\) Co., Ltd. \(PSBS\)](#)



UL94 V-0 RATED FLAME RETARDANT CASING/HOUSING

This product's casing/housing is classed UL94 V-0. In simple terms, this means that the casing/housing is considered flame retardant in accordance with the plastics flammability standard.

Data Sheet

